



ART REV : 7'

REV	DATE	BY	CHK'D	DESCRIPTION
5	03/07/97	MAG		CHG'D 23-926-01 TO 23-926-02 PER ECO 970100.
4	01/18/95	JCJ		CORRECTED REFERENCE DESIGNATORS PER ECO# E0520
3	12/15/94	REM		ART TO REV. 7, CHANGED HEADPHONE CIRCUIT PER E489. NO CHG TO PARTS PLACEMENT OR VALUE.
2	03/04/94	REM		NO CHANGE TO PARTS LIST; ART TO REV. 2.
1	04/07/93	REM		R22 CHG'D FROM 22K TO 10K CHG'D R24 TO:76-100-01 & R25 TO:76-472-01

SIGNATURES:		DATE:	11880 BORMAN DR. ST. LOUIS, MISSOURI 63146	
DRAWN:	MGA	03/13/93	PROJECT NAME: GX-30M GUITAR AMP	
CHK'D:			DRAWING NAME: PICTORIAL DRAWING	
APP'D:			DRAWING NO. 07P202-01 REV. 5	
ORIGINAL ISSUED:	04/07/93		SCALE: 1:1 SHEET: 1 OF 2	
PLOT DATE:	03/20/97			
PLOT TIME:	07:27:28			
FILE NAME:	20201P5_			

DESIGNATOR	PART #	DESCRIPTION							
C1	10A101-21	100pF	200V	HDW1	30-440-52	HTSINK SCREW	R32	76-222-01	2. 2K
C2	10A102-11	. 001uF	100V	HDW2	30-440-52	HTSINK SCREW	R33	76-104-01	100K
C3	12A106-11	10uF	16V	HDW3	30-442-52	HTSINK NUT	R34	76-104-01	100K
C4	10A104-01	. 1uF	50V	HDW4	30-442-52	HTSINK NUT	R35	76-392-01	3. 9K
C5	10A471-11	470pF	100V	HDW5	30-408-52	TD-220 SCREW	R36	76-334-01	330K
C6	12A106-11	10uF	16V	HDW6	30-442-52	TD-220 NUT	R37	76-183-01	18K
C7	10A104-01	. 1uF	50V	HDW7	35-043-01	TD-220 SHOULDER BUSHING	R38	76-103-01	10K
C8	12A335-51	3. 3uF	50V	HDW8	35-575-01	TD-220 SIL-PAD	R39	76-103-01	10K
C9	10A222-01	. 0022uF	50V				R40	76-104-01	100K
C10	10A104-01	. 1uF	50V	IC1	37-074-01	TL074	R41	76-472-01	4. 7K
C11	10A104-01	. 1uF	50V	IC2	37-532-01	NE5532	R42	76-682-01	6. 8K
C12	10A104-01	. 1uF	50V	IC3	37-532-01	NE5532	R43	76-472-01	4. 7K
C13	10A223-01	. 022uF	50V	IC4	37-307-01	MN3007	R44	76-471-01	470
C14	10A222-01	. 0022uF	50V	IC5	37-301-01	MN3101	R45	76-105-01	1M
C15	12A225-51	2. 2uF	50V	IC6	37-532-01	NE5532	R46	76-222-01	2. 2K
C16	12A105-51	1uF	50V	IC7	37-250-01	TDA2050H	R47	76-103-01	10K
C17	10A150-21	15pF	200V	J1	39-116-01	T/S	R48	76-273-01	27K
C18	10A104-01	. 1uF	50V	J2	39-117-01	T/R/S	R49	76-103-01	10K
C19	10A333-01	. 033uF	50V	J3	39-117-01	T/R/S	R50	76-331-01	330
C20	12A105-51	1uF	50V	J4	39-116-01	T/S	R51	76-331-01	330
C21	10A104-01	. 1uF	50V				R52	76-224-01	220K
C22	10A104-01	. 1uF	50V	J5	17-102-02	CONN	R53	76-224-01	220K
C23	10A153-01	. 015uF	50V	J6	17-102-02	CONN	R54	76-224-01	220K
C24	10A104-01	. 1uF	50V	J7	17-309-02	CONN	R55	76-224-01	220K
C25	10A330-21	33pF	200V	J8	17-894-01	TAB	R56	76-103-01	10K
C26	10A105-51	1. 0uF	50V	J9	17-894-01	TAB	R57	76-222-01	2. 2K
C27	10A332-01	. 0033uF	50V	J10	17-894-01	TAB	R58	76-333-01	33K
C28	10A222-01	. 0022uF	50V	J11	17-894-01	TAB	R59	76-331-01	330
C29	10A333-01	. 033uF	50V	J12	17-894-01	TAB	R60	76-331-01	330
C30	10A104-01	. 1uF	50V	J13	17-894-01	TAB	R61	76-470-01	47
C31	12-476-81	47uF	16V	J14	17-894-01	TAB	R62	78-001-03	0. 1 3W
C32	10A104-01	. 1uF	50V	J15	17-500-01	GND LUG	R63	76-010-01	1
C33	10A104-01	. 1uF	50V				R64	76-471-01	470
C34	10A471-11	470pF	100V	JW1-21	76-000-01	JUMPER WIRE	R65	76-470-01	47
C35	12-476-32	47uF	35V				R66	76-331-01	330
C36	12-476-32	47uF	35V	P1	70-254-61	250K	R67	76-331-01	330
C37	10A101-21	100pF	200V	P2	70-103-68	10KA	R68	77-221-01	220 1/2W
C38	12A106-11	10uF	16V	P3	70-254-61	250K	R69	77-221-01	220 1/2W
C39	10A223-01	. 022uF	50V	P4	70-103-68	10KA	R70	77-152-01	1. 5K 1/2W
C40	10-224-03	. 22uF	100V	P5	70-103-68	10KA	R71	77-561-01	560 1/2W
C41	10A104-01	. 1uF	50V	P6	70-501-62	500A	R72	76-223-01	22K
C42	10-332-01	. 0033uF	U. L.	P7	70-103-61	10KL	R73	76-331-01	330
C43	12-478-25	4700uF	25V	P8	70-103-68	10KA	R74	76-331-01	330
C44	12-478-25	4700uF	25V	P9	70-103-61	10KL	R75	76-103-01	10K
C45	12A335-51	3. 3uF	50V	P10	70-104-63	100KRA	R76	76-223-01	22K
C46	12A335-51	3. 3uF	50V						
C47	12A106-11	10uF	16V	Q1	96-112-01	J112	SW1	88-302-01	DPDT SWITCH
C48	12A106-11	10uF	16V	Q2	96-112-01	J112	SW2	88-302-01	DPDT SWITCH
C49	12-107-32	100uF	35V	Q3	96-112-01	J112			
C50	12A335-51	3. 3uF	50V	Q4	96-112-01	J112			
C51	12A335-51	3. 3uF	50V						
C52	10A104-01	. 1uF	50V	RC-1	99-124-02	12_PIN RIBBON			
C53	12A335-51	3. 3uF	50V	R1	76-222-01	2. 2K			
C54	12A335-51	3. 3uF	50V	R2	76-274-01	270K			
C55	10A221-11	220pF	100V	R3	76-332-01	3. 3K			
C56	10A222-01	. 0022uF	50V	R4	76-102-01	1K			
C57	10A104-01	. 1uF	50V	R5	76-471-01	470			
C58	10A152-11	. 0015uF	100V	R6	76-103-01	10K			
				R7	76-471-01	470			
				R8	76-223-01	22k			
D1	21A914-01	1N914		R9	76-223-01	22k			
D2	21A914-01	1N914		R10	76-472-01	4. 7K			
D3	21A146-01	1N746		R11	76-474-01	470K			
D4	21A754-01	1N754	6. 8V	R12	76-473-01	47K			
D5	21A914-01	1N914		R13	76-473-01	47K			
D6	21A146-01	1N746		R14	76-471-01	470			
D7	21A754-01	1N754	6. 8V	R15	76-103-01	10K			
D8	21A914-01	1N914		R16	76-103-01	10K			
D9	21A914-01	1N914		R17	76-105-01	1M			
D10	21A914-01	1N914		R18	76-332-01	3. 3K			
D11	21A402-01	1N4002		R19	76-103-01	10K			
D12	21A402-01	1N4002		R20	76-474-01	470K			
				R21	76-153-01	15K			
				R22	76-103-01	10K			
				R23	76-223-01	22k			
				R24	76-100-01	10			
				R25	76-472-01	4. 7K			
				R26	76-331-01	330			
				R27	76-471-01	470			
				R28	76-101-01	100			
				R29	76-103-01	10K			
				R30	76-102-01	1K			
				R31	76-472-01	4. 7K			
D13	21A192-01	1N5392							
D14	21A192-01	1N5392							
D15	21A192-01	1N5392							
D16	21A192-01	1N5392							
D17	21A444-01	1N4744 15V							
D18	21A444-01	1N4744 15V							
D19	21-573-01	5 mm SQUARE RED LED							
D20	21A444-01	1N4744 15V							
FC1	23-926-02	CLIP							
FC2	23-926-02	CLIP							
F1	23-301-05	1A SLD-BLD FUSE							
HS1	33-133-51	HEATSINK							

5	03/07/97	MAG		CHG'D 23-926-01 TO 23-926-02 PER ECO 970100.
4	01/18/95	JCJ		CORRECTED REFERENCE DESIGNATORS PER ECO# E0520
3	12/15/94	REM		ART TO REV. 7, CHANGED HEADPHONE CIRCUIT PER E489. NO CHG TO PARTS PLACEMENT OR VALUE.
2	03/04/94	REM		NO CHANGE TO PARTS LIST; ART TO REV. 2.
1	04/07/93	REM		R22 CHG'D FROM 22K TO 10K CHG'D R24 TO:76-100-01 & R25 TO:76-472-01
REV	DATE	BY	CHK'D	DESCRIPTION
SIGNATURES:		DATE:		  11880 BORMAN DR. ST. LOUIS, MISSOURI 63146
DRAWN:	MGA	03/13/93		
CHK'D:				PROJECT NAME:
APP'D:				GX-30M GUITAR AMP
ORIGINAL ISSUED:	04/07/93			DRAWING NAME:
PLOT DATE:	03/20/97			PICTORIAL DRAWING
PLOT TIME:	07:27:28			DRAWING NO. 07P202-01 REV. 5
FILE NAME:	20201P5_			SCALE: 1:1 SHEET: 2 OF 2